

Adding RISCO PRO Camera

ADD CAMERA 08EDED845D24 (2/3)	
CAMERA NAME	08EDED845D24
CAMERA TYPE	RISCO Pro
	Username
	Password
MAC ADDRESS	08EDED845D24
IP ADDRESS	192.168.0.21
NVR	Recording: <input type="radio"/> Continuous <input type="radio"/> Motion Detected
<input type="button" value="Save & Continue"/> <input type="button" value="Cancel"/>	

Figure 13 Adding RISCO Pro Camera

1. Enter the Username and Password. The Username is “admin”. The default Password is “_AdmiN_ MAC address” (for example, _AdmiN_AABBCCDDEEFF).

NOTE: For enhanced security, it is recommended to change the default password.

2. Recording Mode: If “Motion Detected” is selected, the NVR will record only if motion is detected by the camera. If “Continuous” is selected, the camera will record continuously.
3. Click Save & Continue. Repeat the procedure for the other cameras until all cameras you have selected for the NVR are setup. The following screen provides a summary of the cameras that have been connected successfully or that failed to be connected to the NVR.

NOTE: RISCO Pro cameras can be viewed via the NVR only, and cannot be installed as standalone cameras.